
Extended Range MetalHead[™] Proximity Sensor



Dimensions



Body Length (mm) 70


Note: The product images shown may change over time as products are updated.

Part Number ECS1-0802N-SRU4-PTFE-100C Features

Inductive Proximity Sensors are used in a wide variety of manufacturing operations where a metal target needs to be sensed. HTM Sensors inductive proximity sensors have a Lifetime Warranty, a CSA or UL approval, and a huge inventory for sameday shipping. For tougher applications where the sensors need more range to stay out of harm's way, or to withstand high temperatures, weld spatter, chemical exposure, oil or other rough environments, HTM Sensors has the widest range of proximity sensors on the market.

Connection

SENSORS





Technical Data

| reennear Data | |
|----------------------------|----------------------------------------|
| Body Style | Cylindrical |
| Sensor Housing Material | Stainless Steel SUS303 |
| Sensor Face Material | 1-Piece Stainless Steel |
| Mounting Style | Shielded |
| Diameter | 8 mm Threaded |
| Sensing Range: | 2 mm Range |
| Output Type: | NPN Output |
| Output Function | NO/NC Switchable Output |
| Connection | 4-Pin Connector |
| Connector Type | M12x1 Quick-Connect |
| Operating Voltage | 10-30 VDC |
| Switching Frequency | 2 KHz |
| Operating Temperature | -20 °C - +100 °C |
| Current Consumption | <10 mA |
| IP Rating: | IP68 |
| EMC Rating | RFI>3V/m / EFT>1kV / ESD>4Kv (contact) |
| Shock Rating: | IEC 60497-5-2 Part 7.4.1&7.4.2 |
| Short Circuit Protected | Yes |
| Reverse Polarity Protected | Yes |
| Max Current | 200 mA |
| Leakage Current | <0.01 mA |
| Surge Current | - |
| Response Time | 0.1 ms/0.1 ms |
| Hysteresis | <15%(Sr) |
| Overload Trip Point | ≥220 mA |
| Weld Field Immune | No |
| Weld Spatter Resistant | Yes - SpatterGuard [™] Coated |
| Body Length (mm) | 70 |
| | |

In the USA: 1889 Maryland Ave., Niagara Falls, NY 14305 In Canada: 3419 Mainway, Burlington, ON L7M 1A9 Toll Free: 1-800-644-1756 • Fax: 888-283-2127 service@htmsensors.com

htmsensors.com